NPort® 5100 Series

1-port RS-232/422/485 serial device servers

- Small size for easy installation
- Real COM/TTY drivers for Windows and Linux
- Standard TCP/IP interface and versatile operation modes
- Easy-to-use Windows utility for configuring multiple device servers
- Built-in 15 kV ESD protection for all serial signals
- SNMP MIB-II for network management
- Configure by Telnet, web browser, or Windows utility
- Adjustable pull high/low resistor for RS-485 ports

Specifications

Ethernet Interface
Number of Ports: 1
Speed: 10/100 Mbps, auto MDI/MDIX
Connector: 8-pin RJ45
Magnetic Isolation Protection: 1.5 kV built-in

Serial Interface
Number of Ports: 1
Serial Standards:
NPort 5110: RS-232
NPort 5130: RS-422/485
NPort 5150: RS-232/422/485
Connector: DB9 male
Serial Line Protection: 15 kV ESD protection for all signals
RS-485 Data Direction Control: ADDC® (automatic data direction control)
Pull High/Low Resistor for RS-485: 1 kΩ, 150 kΩ

Serial Communication Parameters
Data Bits: 5, 6, 7, 8
Stop Bits: 1, 1.5, 2
Parity: None, Even, Odd, Space, Mark
Flow Control: RTS/CTS and DTR/DSR (RS-232 only), XON/XOFF
Baudrate:
NPort 5110: 110 bps to 230.4 kbps
NPort 5130/5150: 50 bps to 921.6 kbps

Serial Signals
RS-232: TxD, RxD, RTS, CTS, DTR, DSR, DCD, GND
RS-422: Tx+, Tx-, Rx+, Rx-, GND
RS-485-4w: Tx+, Tx-, Rx+, Rx-, GND
RS-485-2w: Data+, Data-, GND

Software
Network Protocols: ICMP, IPv4, TCP, UDP, DHCP, BOOTP, Telnet, DNS, SNMP V1, HTTP, SMTP
Configuration Options: Web Console, Serial Console (NPort 5110/5150 only), Telnet Console, Windows Utility
Windows Real COM Drivers: Windows 95/98/ME/NT/2000, Windows XP/2003/Vista/2008/7/8/8.1 (x86/x64), Windows 2008 R2/2012/2012 R2 (x64), Windows Embedded CE 5.0/6.0, Windows XP Embedded
Fixed TTY Drivers: SCO Unix, SCO OpenServer, UnixWare 7, QNX 4.25, QNX 6, Solaris 10, FreeBSD, AIX 5.x, HP-UX 11i, Mac OS X
Linux Real TTY Drivers: Linux 2.4.x, 2.6.x, 3.x

Physical Characteristics
Housing: Metal
Weight: 340 g
Dimensions:
Without ears: 52 x 80 x 22 mm (2.05 x 3.15 x 0.87 in)
With ears: 75.2 x 80 x 22 mm (2.96 x 3.15 x 0.87 in)

Environmental Limits
Operating Temperature:
Standard Models: 0 to 55°C (32 to 131°F)
Wide Temp. Models: -40 to 75°C (-40 to 167°F)
Storage Temperature: -20 to 75°C (-4 to 167°F)
Ambient Relative Humidity: 5 to 95% (non-condensing)
Altitude: Up to 2000 m
Note: Please contact Moxa if you require products guaranteed to function properly at higher altitudes.

Power Requirements
Input Voltage: 12 to 48 VDC
Power Consumption:
NPort 5110: 128.7 mA @ 12 V, 72 mA @ 24 V
NPort 5130/5150: 200 mA @ 12 V, 106 mA @ 24 V

Standards and Certifications
Safety: UL 60950-1, EN 60950-1
EMC: CE, FCC
EMI: EN 55022 Class A, FCC Part 15 Subpart B Class A
EMS: EN 55024

Reliability
Automatic Reboot Trigger: Built-in WDT (watchdog timer)
MTBF (mean time between failures):
NPort 5110: 279,122 hrs
NPort 5130: 246,505 hrs
NPort 5150: 246,034 hrs

Warranty
Warranty Period: 5 years
Details: See www.moxa.com/warranty

Appearance

Dimensions

Unit: mm (inch)

NPort® 5110

NPort® 5130

NPort® 5150

Pin Assignment

DB9 male connector

NPort® 5110 (RS-232)

PIN	RS-232
1	DCD
2	RxD
3	TxD
4	DTR
5	GND
6	DSR
7	RTS
8	CTS

NPort® 5130 (RS-422/485)

PIN	RS-422/485-4w	RS-485-2w
1	TxD-(A)	–
2	TxD+(B)	–
3	RxD+(B)	Data+(B)
4	RxD-(A)	Data-(A)
5	GND	GND
6	–	–
7	–	–
8	–	–

NPort® 5150 (RS-232/422/485)

PIN	RS-232	RS-422/485-4w	RS-485-2w
1	DCD	TxD-(A)	–
2	RxD	TxD+(B)	–
3	TxD	RxD+(B)	Data+(B)
4	DTR	RxD-(A)	Data-(A)
5	GND	GND	GND
6	DSR	–	–
7	RTS	–	–
8	CTS	–	–

Ordering Information

Available Models

NPort 5110: 1-port RS-232 device server, 0 to 55°C operating temperature
NPort 5130: 1-port RS-422/485 device server, 0 to 55°C operating temperature
NPort 5150: 1-port RS-232/422/485 device server, 0 to 55°C operating temperature
NPort 5110-T: 1-port RS-232 device server, -40 to 75°C operating temperature

Optional Accessories (can be purchased separately)

DK-35A: Mounting kit for 35-mm DIN-Rail

Package Checklist

- NPort 5100 device server
- 100 to 240 VAC power adapter (excluding T models)
- Documentation and software CD
- Quick installation guide (printed)
- Warranty card

© Moxa Inc. All Rights Reserved. Updated Mar. 28, 2014. Specifications subject to change without notice. Please visit our website for the most up-to-date product information.